

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION	DATE	BY	
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR

STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES
EDR-83 POLE ID: 3371	210+02	323		(970) 336.4 ACSR (Merlin) (323) 4/0 ACSR (Penguin) (110) 2 AWG Triplex (Conch)	(1) 45-1	(1) C6.21F (1) S1.3	(1) J2.1	(1) G1.5		(1) TM-10-MA01	(1) H1.1	(1) E1.1 (1) F2.8		(1) M.FIBER	TAP OFF OF A PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS STRINGING LOCATION MOUNT S1.3 ON CROSSARM
EDR-84 POLE ID: 20452	213+25	307		(920) 336.4 ACSR (Merlin) (307) 4/0 ACSR (Penguin)	(1) 55-2	(1) CAL-1 (1) A5.3NG (1) S1.1				(1) TM-10-MA01		(2) E1.1 (2) F2.8		(1) M.FIBER	TAP OFF OF C PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY HILL- EMBED 8.5 FEET
EDR-85 POLE ID: 20451	216+32	183		(548) 336.4 ACSR (Merlin) (183) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER	
EDR-86 POLE ID: 3442	218+15	238		(713) 336.4 ACSR (Merlin) (238) 4/0 ACSR (Penguin)	(2) 50-2	(1) Y1.3	(1) J2.1	(1) G1.5		(2) TM-10-MA01	(2) H1.1			(1) M.FIBER	TAP OFF OF A PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS
EDR-87 POLE ID: 3446	220+52	175		(525) 336.4 ACSR (Merlin) (175) 4/0 ACSR (Penguin) (75) 4/0 AWG Triplex (Sweetbriar)	(1) 45-2	(1) CAL-1	(1) J2.1	(1) G1.5	(1) UA1.2 (1) US1.PJ (55) 2AWG ALUMINUM URD CABLE	(1) TM-10-MA01	(1) H1.1			(1) M.FIBER	TAP OFF OF C PHASE OVERHEAD TAP OFF OF B PHASE UNDERGROUND TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS
EDR-88 POLE ID: 3450	222+27	219		(657) 336.4 ACSR (Merlin) (219) 4/0 ACSR (Penguin) (140) 4 AWG ACSR (Swanate)	(1) 45-2	(1) CAL-1 (1) A5.3NG (1) S1.1				(1) TM-10-MA01		(2) E1.1 (2) F2.8		(1) M.FIBER	TAP OFF OF A PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY
EDR-89 POLE ID: 20450	224+46	338		(1013) 336.4 ACSR (Merlin) (338) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1 (1) RE: A5.3NG (1) RE: S1.1	(1) RE: J2.1	(1) RE: G1.5						(1) M.FIBER	TAP OFF OF A PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY REPLACE SECONDARY AND COMMUNICATION TAP POLE
EDR-90 POLE ID: 20449 POLE ID:3458	227+84	317	12° 47 ' 15" LT	(950) 336.4 ACSR (Merlin) (317) 4/0 ACSR (Penguin)	(1) EX: 50-2 (1) 40-2	(1) RE: C6.21F (1) RE: A5.3NG (1) RE: S1.1	(1) RE: J2.1 (1) J2.1	(1) RE: G1.5	(1) RE:UA1.2	(1) TM-10-MA01		(3) E1.1 (3) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF C PHASE OVERHEAD TAP OFF OF B PHASE UNDERGROUND STRINGING LOCATION MOUNT S1.1 FOR TAP ON CROSSARM REPLACE TAP POLE
EDR-91 POLE ID: 3460	231+01	159	20° 11 ' 3" LT	(477) 336.4 ACSR (Merlin) (159) 4/0 ACSR (Penguin) (135) 2 AWG Triplex (Conch)	(1) 60-2	(1) C3.1 (3) MS3.1-4.1	(1) J2.1	(1) G1.5		(1) TM-10-MA01	(1) H1.1	(3) E1.1 (3) F2.8		(1) M.FIBER	TAP OFF OF C PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS
EDR-92 POLE ID: 3462	232+60	225		(675) 336.4 ACSR (Merlin) (225) 4/0 ACSR (Penguin) (100) 2 AWG Triplex (Conch)	(1) 45-2	(1) CAL-1	(1) J2.1	(1) G1.5		(1) TM-10-MA01	(1) H1.1	(2) E1.1 (2) F2.8		(1) M.FIBER	TAP OFF OF C PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS
EDR-93 POLE ID: 20448	234+85	252		(756) 336.4 ACSR (Merlin) (252) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1 (1) RE: A5.3NG (1) RE: S1.1								(1) M.FIBER	TAP OFF OF B PHASE OVERHEAD TAP OFF OF C PHASE UNDERGROUND MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY
EDR-94 POLE ID: 20355	237+37	242	4° 57 ' 22" RT	(726) 336.4 ACSR (Merlin) (242) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-6								(1) M.FIBER	

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET												A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES	
EDR-95 POLE ID: 20447	239+79	301	8° 47 ' 38" RT	(903) 336.4 ACSR (Merlin) (301) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L (3) MS3.1-4.1	(1) RE: J2.1	(1) RE: G1.5				(3) E1.4		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF C PHASE	
EDR-96 POLE ID: 20441	242+80	217	4° 57 ' 0" RT	(652) 336.4 ACSR (Merlin) (217) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) C4.1G						(3) E1.4		(1) M.FIBER	STRINGING LOCATION	
EDR-97 POLE ID: 3519	244+97	306	11° 36 ' 18" RT	(918) 336.4 ACSR (Merlin) (306) 4/0 ACSR (Penguin)	(1) 60-2	(1) C3.1L				(1) TM-10-MA01		(3) E1.4		(1) M.FIBER	HILL- EMBED 9 FEET ROCKY AREA- CUT AND KICK	
EDR-98 POLE ID: 3521	248+03	207		(622) 336.4 ACSR (Merlin) (207) 4/0 ACSR (Penguin)	(1) 50-2	(1) C1.13F				(1) TM-10-MA01				(1) M.FIBER	HILL- EMBED 8 FEET	
EDR-99 POLE ID: 20438	250+10	190		(571) 336.4 ACSR (Merlin) (190) 4/0 ACSR (Penguin)	(1) EX: 50-3	(1) RE: CAL-1								(1) M.FIBER		
EDR-100 POLE ID: 20442	252+01	203		(608) 336.4 ACSR (Merlin) (203) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1			(2) RE:UA1.2					(1) M.FIBER		
EDR-101 POLE ID: 20444	254+04	213	2° 10 ' 11" LT	(639) 336.4 ACSR (Merlin) (213) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-6	(1) RE: J2.1	(2) RE: G1.5						(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF A PHASE	
EDR-102 POLE ID: 20437	256+16	139		(416) 336.4 ACSR (Merlin) (139) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: C6.21F (1) RE: R3.3								(1) M.FIBER	STRINGING LOCATION PHASING FOR RECLOSER IS C-B-A FIELD TO ROAD	
EDR-103 POLE ID: 5802	257+55	139		(417) 336.4 ACSR (Merlin) (139) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1 (1) RE: S1.3	(1) RE: J2.1	(3) RE: G1.5						(1) M.FIBER	TAP OFF OF A PHASE REUSE EXISTING S1.3 MOUNTING BRACKET	
EDR-104 POLE ID: 24036	258+94	272		(817) 336.4 ACSR (Merlin) (272) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1	(1) RE: J2.1	(1) RE: G1.5						(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF A PHASE	
EDR-105 POLE ID: 24035	261+67	264	2° 50 ' 54" RT	(791) 336.4 ACSR (Merlin) (264) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER		
EDR-106 POLE ID: 24034	264+30	341	4° 26 ' 18" RT	(1024) 336.4 ACSR (Merlin) (341) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER		

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET												A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES	
EDR-107 POLE ID: 20432	267+72	235		(705) 336.4 ACSR (Merlin) (235) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER		
EDR-108 POLE ID: 20430	270+07	362	2° 32 ' 31" LT	(1087) 336.4 ACSR (Merlin) (362) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER		
EDR-109 POLE ID: 20428	273+69	244	9° 12 ' 47" LT	(731) 336.4 ACSR (Merlin) (244) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) C4.1G (3) MS3.1-4.1	(1) RE: J2.1	(1) RE: G1.5				(3) E1.1 (3) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF C PHASE STRINGING LOCATION	
EDR-110 POLE ID: 20433	276+13	289		(866) 336.4 ACSR (Merlin) (289) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1	(1) RE: J2.1	(1) RE: G1.5						(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF A PHASE	
EDR-111 POLE ID: 20431 POLE ID: 5394	279+02	229	9° 5 ' 19" RT	(688) 336.4 ACSR (Merlin) (229) 4/0 ACSR (Penguin)	(1) EX: 45-2 (1) 35-2	(1) C3.1L	(2) RE: J2.1 (1) J2.1	(1) RE: G1.5	(1) RE:UA1.2	(1) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF B PHASE REPLACE STUB POLE	
EDR-112 POLE ID: 20426	281+31	289	11° 30 ' 57" RT	(868) 336.4 ACSR (Merlin) (289) 4/0 ACSR (Penguin)	(1) 55-2	(1) C3.1L				(1) TM-10-MA01		(3) E1.4		(1) M.FIBER	HILL- EMBED 8.5 FEET	
EDR-113 POLE ID: 20425 POLE ID: 3458	284+20	232		(695) 336.4 ACSR (Merlin) (232) 4/0 ACSR (Penguin)	(1) EX: 50-2 (1) 35-2	(1) RE: CAL-6 (1) RE: A5.3NG (1) RE: S1.1	(1) RE: J2.1	(1) RE: G1.5		(1) TM-10-MA01		(1) E1.1 (1) E1.4 (1) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF C PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY REPLACE STUB POLE	
EDR-114 POLE ID: 20424	286+52	228		(685) 336.4 ACSR (Merlin) (228) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-6								(1) M.FIBER		
EDR-115 POLE ID: 20423	288+80	316	2° 31 ' 30" RT	(947) 336.4 ACSR (Merlin) (316) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) C4.1G								(1) M.FIBER		
EDR-116 POLE ID: 20422	291+96	287	2° 6 ' 57" RT	(862) 336.4 ACSR (Merlin) (287) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-6								(1) M.FIBER		
EDR-117 POLE ID: 20421 POLE ID: NEW STR	294+83	330	2° 29 ' 27" RT	(991) 336.4 ACSR (Merlin) (330) 4/0 ACSR (Penguin)	(1) EX: 50-2 (1) 35-2	(1) RE: CAL-2				(1) TM-10-MA01		(1) E1.1 (1) E1.4 (1) F2.8		(1) M.FIBER	INSTALL NEW STUB POLE	
EDR-118 POLE ID: 20420	298+14	326		(977) 336.4 ACSR (Merlin) (326) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: C6.21F								(1) M.FIBER	STRINGING LOCATION	

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-119 POLE ID: 20419	301+39	224	7° 7 ' 6" LT	(671) 336.4 ACSR (Merlin) (224) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: C6.21F								(1) M.FIBER	STRINGING LOCATION		
EDR-120 POLE ID: 20418	303+63	301	13° 44 ' 16" LT	(903) 336.4 ACSR (Merlin) (301) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1						(3) E1.1		(1) M.FIBER			
EDR-121 POLE ID: 20415	306+64	327	5° 31 ' 22" LT	(981) 336.4 ACSR (Merlin) (327) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-2								(1) M.FIBER			
EDR-122 POLE ID: 20417	309+91	156		(469) 336.4 ACSR (Merlin) (156) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1 (1) RE: A5.3NG (1) RE: S1.1								(1) M.FIBER	TAP OFF OF A PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY		
EDR-123 POLE ID: 5611	311+47	172		(515) 336.4 ACSR (Merlin) (172) 4/0 ACSR (Penguin)	(1) 45-2	(1) C6.21F (1) TR: S2.32				(1) TM-10-MA01	(1) H1.1			(1) M.FIBER	TRANSFER SWITCH TO NEW POLE STRINGING LOCATION		
EDR-124 POLE ID: 20416	313+19	271		(814) 336.4 ACSR (Merlin) (271) 4/0 ACSR (Penguin)	(1) EX: 55-2	(1) RE: CAL-1								(1) M.FIBER			
EDR-125 POLE ID: 20414	315+90	317		(951) 336.4 ACSR (Merlin) (317) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-6								(1) M.FIBER			
EDR-126 POLE ID: 20413	319+07	165		(496) 336.4 ACSR (Merlin) (165) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-6								(1) M.FIBER			
EDR-127 POLE ID: NEW STR	320+73	139		(417) 336.4 ACSR (Merlin) (139) 4/0 ACSR (Penguin)	(1) 45-2	(1) CAL-1				(1) TM-10-MA01				(1) M.FIBER	HILL- EMBED 7.5 FEET		
EDR-128 POLE ID: 20412	322+12	316	9° 22 ' 45" LT	(948) 336.4 ACSR (Merlin) (316) 4/0 ACSR (Penguin)	(1) 50-2	(1) C3.1L				(1) TM-10-MA01		(3) E1.1 (3) F2.8		(1) M.FIBER	HILL- EMBED 8 FEET		
EDR-129 POLE ID: 20411	325+28	280	6° 41 ' 49" LT	(841) 336.4 ACSR (Merlin) (280) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) C3.1L						(3) E1.1 (3) F2.8		(1) M.FIBER			
EDR-130 POLE ID: 20410 POLE ID: 3565	328+08	238	8° 38 ' 23" RT	(714) 336.4 ACSR (Merlin) (238) 4/0 ACSR (Penguin)	(1) 65-2 (1) 45-2	(1) C3.1L				(2) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE. HILL- EMBED 9 FEET		

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-131 POLE ID: 20409	330+46	302		(907) 336.4 ACSR (Merlin) (302) 4/0 ACSR (Penguin)	(1) 60-1	(1) CAL-1				(1) TM-10-MA01				(1) M.FIBER			
EDR-132 POLE ID: 20408 POLE ID: 3568	333+48	263	7° 1 ' 36" RT	(790) 336.4 ACSR (Merlin) (263) 4/0 ACSR (Penguin)	(1) EX: 50-2 (1) 35-2	(1) C3.1L				(1) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE.		
EDR-133 POLE ID: 5211 POLE ID: 3570	336+12	295	5° 16 ' 57" RT	(885) 336.4 ACSR (Merlin) (295) 4/0 ACSR (Penguin)	(1) 50-2 (1) 40-2	(1) C4.1G				(2) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE STRINGING LOCATION		
EDR-134 POLE ID: 5810	339+07	295		(884) 336.4 ACSR (Merlin) (295) 4/0 ACSR (Penguin)	(1) EX: 45-3	(1) RE: CAL-1								(1) M.FIBER			
EDR-135 POLE ID: 5992	342+01	306		(917) 336.4 ACSR (Merlin) (306) 4/0 ACSR (Penguin)	(1) 45-2	(1) C1.13F				(1) TM-10-MA01				(1) M.FIBER	HILL- EMBED 7.5 FEET		
EDR-136 POLE ID: 20407	345+07	314		(941) 336.4 ACSR (Merlin) (314) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER			
EDR-137 POLE ID: 20406	348+21	327		(982) 336.4 ACSR (Merlin) (327) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-1								(1) M.FIBER			
EDR-138 POLE ID: 20318	351+48	312		(936) 336.4 ACSR (Merlin) (312) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1								(1) M.FIBER			
EDR-139 POLE ID: 20405 POLE ID: NEW STR	354+60	282	2° 24 ' 44" RT	(845) 336.4 ACSR (Merlin) (282) 4/0 ACSR (Penguin)	(1) 65-2 (1) 40-2	(1) CAL-2				(2) TM-10-MA01		(1) E1.1 (1) E1.4 (1) F2.8		(1) M.FIBER	INSTALL NEW STUB POLE HILL- EMBED 9.5 FEET		
EDR-140 POLE ID: 20404	357+42	285		(856) 336.4 ACSR (Merlin) (285) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) CAL-1						(1) E1.1		(1) M.FIBER			
EDR-141 POLE ID: 20403	360+27	277		(830) 336.4 ACSR (Merlin) (277) 4/0 ACSR (Penguin)	(1) 50-2	(1) CAL-1				(1) TM-10-MA01				(1) M.FIBER	HILL- EMBED 8 FEET		
EDR-142 POLE ID: 20402	363+04	337		(1010) 336.4 ACSR (Merlin) (337) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C6.21F (1) RE: A5.3NG (1) RE: S1.1 (1) RE: S2.32						(1) E1.1 (1) F2.8		(1) M.FIBER	MOUNT A5.3NG ONTO ROAD SIDE PHASE OF CROSSARM WITH EYE NUT TAP OFF OF C PHASE STRINGING LOCATION REPLACE SWITCH JUMPERS AND CLAMPS, REUSE EXISTING SWITCH		

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-143 POLE ID: 3583	366+40	281		(843) 336.4 ACSR (Merlin) (281) 4/0 ACSR (Penguin)	(1) 50-2	(1) C6.21F				(1) TM-10-MA01				(1) M.FIBER	STRINGING LOCATION		
EDR-144 POLE ID: 20496	369+21	245	5° 28 ' 21" LT	(734) 336.4 ACSR (Merlin) (245) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L (3) MS3.1-4.1	(1) RE: J2.1	(1) RE: G1.5	(1) RE:UA1.2			(3) E1.1 (3) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF C PHASE		
EDR-145 POLE ID: 20401	371+66	387	15° 21 ' 56" LT	(1161) 336.4 ACSR (Merlin) (387) 4/0 ACSR (Penguin)	(1) 60-2	(1) C3.1				(1) TM-10-MA01		(3) E1.1 (3) F2.8		(1) M.FIBER			
EDR-146 POLE ID: 20497	375+53	341		(1024) 336.4 ACSR (Merlin) (341) 4/0 ACSR (Penguin)	(1) 55-1	(1) C1.13F				(1) TM-10-MA01				(1) M.FIBER			
EDR-147 POLE ID: NO#	378+95	330		(991) 336.4 ACSR (Merlin) (330) 4/0 ACSR (Penguin) (130) 2 AWG Triplex (Conch)	(1) 55-1	(1) C1.13F	(1) J2.1	(1) G1.5		(1) TM-10-MA01	(1) H1.1			(1) M.FIBER	TAP OFF OF C PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS		
EDR-148 POLE ID: 20500	382+25	320		(959) 336.4 ACSR (Merlin) (320) 4/0 ACSR (Penguin)	(1) EX: 55-1	(1) RE: CAL-1								(1) M.FIBER			
EDR-149 POLE ID: 20397	385+45	357	15° 36 ' 3" RT	(1070) 336.4 ACSR (Merlin) (357) 4/0 ACSR (Penguin)	(1) 60-2	(1) C4.1G				(1) TM-10-MA01		(3) E1.1 (3) F2.8		(1) M.FIBER	STRINGING LOCATION		
EDR-150 POLE ID: 20501	389+02	260	17° 10 ' 32" RT	(780) 336.4 ACSR (Merlin) (260) 4/0 ACSR (Penguin) (85) 4 AWG ACSR (Swanate)	(1) 60-2	(1) C3.1 (1) A5.3NG (1) S1.1	(1) UK2.1 (1) UK5	(1) G1.5		(1) TM-10-MA01	(1) H1.1	(3) E1.1 (3) F2.8		(1) M.FIBER	TAP OFF OF A PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY		
EDR-151 POLE ID: 20499	391+62	292	2° 14 ' 43" RT	(875) 336.4 ACSR (Merlin) (292) 4/0 ACSR (Penguin)	(1) EX: 55-1	(1) RE: CAL-1 (1) RE: A5.3NG (1) RE: S1.1	(2) RE: UK2.1	(1) RE: G1.5						(1) M.FIBER	TAP OFF OF C PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY		
EDR-152 POLE ID: 20354	394+53	348	33° 50 ' 35" LT	(1043) 336.4 ACSR (Merlin) (348) 4/0 ACSR (Penguin)	(1) EX: 55-1	(1) C3.1 (3) MS3.1-4.1	(1) RE: J2.1	(1) RE: G1.5				(3) E1.1 (3) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF B PHASE		
EDR-153 POLE ID: 20396	398+01	226	29° 28 ' 57" RT	(679) 336.4 ACSR (Merlin) (226) 4/0 ACSR (Penguin)	(1) 60-1	(1) C3.1 (3) MS3.1-4.1	(1) J2.1 (1) UK2.1 (1) UK5	(1) G1.5		(1) TM-10-MA01	(1) H1.1	(3) E1.1 (3) F2.8		(1) M.FIBER	TAP OFF OF C PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS		
EDR-154 POLE ID: 20400	400+28	292	5° 20 ' 36" LT	(875) 336.4 ACSR (Merlin) (292) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L						(3) E1.1 (3) F2.8		(1) M.FIBER			

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-155 POLE ID: 20502	403+19	254		(763) 336.4 ACSR (Merlin) (254) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-6								(1) M.FIBER			
EDR-156 POLE ID: 20399 POLE ID: 3654	405+73	282	7° 18 ' 24" RT	(846) 336.4 ACSR (Merlin) (282) 4/0 ACSR (Penguin)	(1) 60-2 (1) 35-2	(1) C3.1L				(2) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE HILL- EMBED 9 FEET		
EDR-157 POLE ID: 20398 POLE ID: 3656	408+55	258	5° 22 ' 8" RT	(773) 336.4 ACSR (Merlin) (258) 4/0 ACSR (Penguin)	(1) 65-2 (1) 45-2	(1) C3.1L				(2) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE HILL- EMBED 9 FEET CUT AND KICK- ROCKY AREA		
EDR-158 POLE ID: 20395	411+13	232	6° 43 ' 23" LT	(696) 336.4 ACSR (Merlin) (232) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-2								(1) M.FIBER			
EDR-159 POLE ID: 20394	413+45	252		(757) 336.4 ACSR (Merlin) (252) 4/0 ACSR (Penguin)	(1) 50-2	(1) CAL-1				(1) TM-10-MA01				(1) M.FIBER	HILL- EMBED 8 FEET		
EDR-160 POLE ID: 20504	415+97	289	5° 36 ' 18" RT	(867) 336.4 ACSR (Merlin) (289) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: C6.21F						(1) E1.1 (1) F2.8		(1) M.FIBER	STRINGING LOCATION		
EDR-161 POLE ID: 20505 POLE ID: 3661	418+86	299	8° 57 ' 23" RT	(898) 336.4 ACSR (Merlin) (299) 4/0 ACSR (Penguin)	(1) 55-2 (1) 35-2	(1) C3.1L				(2) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE HILL- EMBED 8.5 FEET DROP NEUTRAL TO 8FT TO CONDUCTOR TO PROVIDE ADEQUATE MIDSPAN CLEARANCE ON AHEAD SPAN		
EDR-162 POLE ID: NO#	421+86	207	24° 12 ' 1" LT	(620) 336.4 ACSR (Merlin) (207) 4/0 ACSR (Penguin)	(1) EX: 55-2	(1) C3.1						(3) E1.1 (3) F2.8		(1) M.FIBER			
EDR-163 POLE ID: 20507	423+93	252	8° 45 ' 18" RT	(757) 336.4 ACSR (Merlin) (252) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C4.1G (3) MS3.1-4.1	(1) RE: UK2.1	(1) RE: G1.5				(3) E1.1 (3) F2.8		(1) M.FIBER	TAP OFF OF C PHASE STRINGING LOCATION		
EDR-164 POLE ID: 20392	426+45	220	2° 13 ' 16" RT	(659) 336.4 ACSR (Merlin) (220) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) RE: CAL-1								(1) M.FIBER			
EDR-165 POLE ID: NO#	428+65	279	19° 8 ' 26" LT	(838) 336.4 ACSR (Merlin) (279) 4/0 ACSR (Penguin)	(1) 55-2	(1) C3.1				(1) TM-10-MA01		(3) E1.1 (3) F2.8		(1) M.FIBER			
EDR-166 POLE ID: 20508 POLE ID: NEW STR	431+44	265	18° 9 ' 7" RT	(795) 336.4 ACSR (Merlin) (265) 4/0 ACSR (Penguin)	(1) 55-2 (1) 35-2	(1) C3.1				(2) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	INSTALL NEW STUB POLE HILL- EMBED 8.5 FEET		

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-167 POLE ID: 20244	434+09	232	9° 29 ' 22" RT	(697) 336.4 ACSR (Merlin) (232) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) C3.1L						(2) E1.1 (2) F2.8		(1) M.FIBER			
EDR-168 POLE ID: 20237	436+41	260	11° 40 ' 6" LT	(779) 336.4 ACSR (Merlin) (260) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L						(3) E1.1 (3) F2.8		(1) M.FIBER			
EDR-169 POLE ID: 20509 POLE ID: NEW STR	439+01	324	3° 54 ' 24" RT	(971) 336.4 ACSR (Merlin) (324) 4/0 ACSR (Penguin)	(1) EX: 45-3 (1) 35-2	(1) RE: CAL-2				(1) TM-10-MA01		(1) E1.1 (1) E1.4 (1) F2.8		(1) M.FIBER	INSTALL NEW STUB POLE		
EDR-170 POLE ID: 20510	442+25	315		(946) 336.4 ACSR (Merlin) (315) 4/0 ACSR (Penguin)	(1) 45-2	(1) CAL-1				(1) TM-10-MA01				(1) M.FIBER			
EDR-171 POLE ID: 5798	445+40	304		(913) 336.4 ACSR (Merlin) (304) 4/0 ACSR (Penguin)	(1) 45-2	(1) C1.13F	(1) J2.1	(1) G1.5		(1) TM-10-MA01				(1) M.FIBER	TAP OFF OF A PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS HILL- EMBED POLE 7.5 FEET		
EDR-172 POLE ID: NO# POLE ID: 3694	448+44	321	3° 53 ' 25" RT	(963) 336.4 ACSR (Merlin) (321) 4/0 ACSR (Penguin)	(1) 50-2 (1) 35-2	(1) C6.21F (1) TR: S2.32				(2) TM-10-MA01	(1) H1.1	(1) E1.1 (2) E1.4 (1) F2.8		(1) M.FIBER	TRANSFER SWITCH TO NEW POLE STRINGING LOCATION REPLACE STUB POLE		
EDR-173 POLE ID: 20393 POLE ID: 3678	451+65	260	9° 6 ' 26" RT	(779) 336.4 ACSR (Merlin) (260) 4/0 ACSR (Penguin)	(1) EX: 50-2 (1) 35-2	(1) C3.1L				(1) TM-10-MA01		(1) E1.1 (3) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE		
EDR-174 POLE ID: 20391 POLE ID: 3680	454+25	154	6° 49 ' 2" RT	(461) 336.4 ACSR (Merlin) (154) 4/0 ACSR (Penguin)	(1) EX: 50-2 (1) 35-2	(1) RE: CAL-2				(1) TM-10-MA01		(1) E1.1 (2) E1.4 (1) F2.8		(1) M.FIBER	REPLACE STUB POLE		
EDR-175 POLE ID: 20390	455+79	279	8° 27 ' 17" RT	(837) 336.4 ACSR (Merlin) (279) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L (1) RE: A5.3NG (1) RE: S1.1 (3) MS3.1-4.1	(1) RE: J2.1	(1) RE: G1.5						(1) M.FIBER	TAP OFF OF B PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY		
EDR-176 POLE ID: 20524	458+58	321	8° 33 ' 51" RT	(963) 336.4 ACSR (Merlin) (321) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L (1) RE: A5.3NG (1) RE: S1.1 (3) MS3.1-4.1								(1) M.FIBER	TAP OFF OF B PHASE MOUNT S1.1 FOR TAP 6 INCHES ABOVE A5.3NG ASSEMBLY		
EDR-177 POLE ID: 20517	461+79	292		(877) 336.4 ACSR (Merlin) (292) 4/0 ACSR (Penguin)	(1) EX: 50-3	(1) RE: CAL-6	(1) RE: J2.1	(1) RE: G1.5						(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF A PHASE		
EDR-178 POLE ID: 20523	464+71	250		(749) 336.4 ACSR (Merlin) (250) 4/0 ACSR (Penguin)	(1) EX: 45-3	(1) RE: CAL-1	(1) RE: J2.1	(1) RE: G1.5						(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF C PHASE		

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES. VERIFY ALL TAP CLAMP SIZES.			NO	REVISION	DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET												A	ISSUED FOR BID	9/4/26	BDR

STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES
EDR-179 POLE ID: 20516	467+21	358		(1073) 336.4 ACSR (Merlin) (358) 4/0 ACSR (Penguin) (70) 1/0 AWG Triplex (Netrina)	(1) 55-1	(1) CAL-2	(1) J2.1	(1) G1.5		(1) TM-10-MA01	(1) H1.1	(1) E1.1 (1) F2.8		(1) M.FIBER	TAP OFF OF C PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS HILL- EMBED 8.5 FEET
EDR-180 POLE ID: 20522 POLE ID: 3709	470+78	293		(880) 336.4 ACSR (Merlin) (293) 4/0 ACSR (Penguin) (50) 2 AWG Triplex (Conch)	(1) 60-1 (1) 35-2	(1) CAL-2	(2) J2.1	(1) G1.5		(2) TM-10-MA01	(1) H1.1	(1) E1.1 (1) F2.8		(1) M.FIBER	TAP OFF OF C PHASE TRANSFER EXISTING XFMR AND REPLACE CLAMPS AND STIRRUPS HILL- EMBED 9 FEET CUT AND KICK REPLACE TAP POLE
EDR-181 POLE ID: 20515	473+72	310		(930) 336.4 ACSR (Merlin) (310) 4/0 ACSR (Penguin)	(1) EX: 45-2	(1) RE: CAL-6								(1) M.FIBER	
EDR-182 POLE ID: 20512	476+82	196	6° 29 ' 32" LT	(589) 336.4 ACSR (Merlin) (196) 4/0 ACSR (Penguin)	(1) EX: 50-2	(1) C3.1L (3) MS3.1-4.1	(1) RE: J2.1	(1) RE: G1.5				(3) E1.1 (3) F2.8		(1) M.FIBER	REPLACE JUMPERS AND CLAMPS FOR EXISTING XFMR TAP OFF OF A PHASE
EDR-183 POLE ID: 3713	478+78	143	14° 27 ' 2" LT	(428) 336.4 ACSR (Merlin) (143) 4/0 ACSR (Penguin)	(1) 50-2	(1) C3.1				(1) TM-10-MA01		(3) E1.1 (3) F2.8		(1) M.FIBER	
EDR-184 POLE ID: 3714	480+21		2° 29 ' 48" LT		(1) EX: 45-2	(1) RE: C6.21F			(1) RE:UC2.2					(1) M.FIBER	TAP ALL 3 PHASES STRINGING LOCATION

MASON COUNTY PUD 1					MASON COUNTY PUD					TOTH & ASSOCIATES					NO.	REVISION					
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE STAKING SHEET															A	ISSUED FOR BID					
QTY	CONDUCTOR & CONDUIT	QTY	POLE CLASS & LENGTH	QTY	PRIMARY DISTRIBUTION ASSEMBLIES	QTY	SECONDARY DISTRIBUTION ASSEMBLIES	QTY	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	QTY	UNDERGROUND DISTRIBUTION ASSEMBLIES	QTY	FOUNDATION & PADS	QTY	GROUNDING ASSEMBLIES	QTY	GUYING & ANCHOR ASSEMBLIES	QTY	CONDUCTOR ACCESSORIES	QTY	MISCELLANEOUS ASSEMBLIES
75	4/0 AWG Triplex (Sweetbriar)	2	EX: 55-2	1	Y1.3	2	UK5	21	RE: G1.5	1	US1.PJ	56	TM-10-MA01	13	H1.1	82	F2.8			102	M.FIBER
27018	4/0 ACSR (Penguin)	3	EX: 55-1	2	TR: S2.32	2	UK2.1	11	G1.5	1	UA1.2					47	E1.4				
225	4 AWG ACSR (Swanate)	2	EX: 50-3	1	S1.3	7	RE: UK2.1			1	RE:UC2.2					86	E1.1				
81051	336.4 ACSR (Merlin)	31	EX: 50-2	3	S1.1	23	RE: J2.1			5	RE:UA1.2										
525	2 AWG Triplex (Conch)	3	EX: 45-3	1	RE: S2.32	14	J2.1			55	2AWG ALUMINUM URD CABLE										
70	1/0 AWG Triplex (Netrina)	23	EX: 45-2	1	RE: S1.3																
		3	65-2	9	RE: S1.1																
		6	60-2	1	RE: R3.3																
		3	60-1	10	RE: CAL-6																
		5	55-2	5	RE: CAL-2																
		3	55-1	22	RE: CAL-1																
		10	50-2	6	RE: C6.21F																
		10	45-2	9	RE: A5.3NG																
		1	45-1	30	MS3.1-4.1																
		3	40-2	3	CAL-2																
		12	35-2	10	CAL-1																
				5	C6.21F																
				6	C4.1G																
				19	C3.1L																
				10	C3.1																
				5	C1.13F																
				3	A5.3NG																

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-83 POLE ID: 3371	210+02	323		(970) 3/0 ACSR (Pigeon) (323) 1/0 ACSR (Raven) (110) 2 AWG Triplex (Conch)	(1) 40-4	(1) C6.21L (1) S1.3	(1) J2.1	(1) G1.5			(1) H1.1	(6) E1.1 (2) F2.8					
EDR-84 POLE ID: 20452	213+25	307		(920) 3/0 ACSR (Pigeon) (307) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-1 (1) A5.3NG (1) S1.1						(2) E1.1 (1) F2.8					
EDR-85 POLE ID: 20451	216+32	183		(548) 3/0 ACSR (Pigeon) (183) 1/0 ACSR (Raven)		(1) CAL-1											
EDR-86 POLE ID: 3442	218+15	238		(713) 3/0 ACSR (Pigeon) (238) 1/0 ACSR (Raven)	(2) 40-3	(1) Y1.3	(1) J2.1	(1) G1.5			(2) H1.1						
EDR-87 POLE ID: 3446	220+52	175		(525) 3/0 ACSR (Pigeon) (175) 1/0 ACSR (Raven) (75) 4/0 AWG Triplex (Sweetbriar)	(1) 45-3	(1) CAL-1	(1) J2.1	(1) G1.5	(1) UA1.2 (55) 2AWG ALUMINUM URD CABLE		(1) H1.1	(1) E1.1 (1) F2.8					
EDR-88 POLE ID: 3450	222+27	219		(657) 3/0 ACSR (Pigeon) (219) 1/0 ACSR (Raven) (140) 4 AWG ACSR (Swanate)	(1) 45-3	(1) CAL-1 (1) A5.3NG (1) S1.1						(2) E1.1 (1) F2.8					
EDR-89 POLE ID: 20450	224+46	338		(1013) 3/0 ACSR (Pigeon) (338) 1/0 ACSR (Raven)		(1) CAL-1 (1) A5.3NG (1) S1.1	(1) J2.1										
EDR-90 POLE ID: 20449 POLE ID:3458	227+84	317	12° 47 ' 15" LT	(950) 3/0 ACSR (Pigeon) (317) 1/0 ACSR (Raven)	(1) 35-5	(1) CAL-2 (1) A5.3NG (1) S1.1	(2) J2.1					(3) E1.1 (1) F2.8					
EDR-91 POLE ID: 3460	231+01	159	20° 11 ' 3" LT	(477) 3/0 ACSR (Pigeon) (159) 1/0 ACSR (Raven) (135) 2 AWG Triplex (Conch)	(1) 45-3	(1) CAL-2	(1) J2.1	(1) G1.5			(1) H1.1	(3) E1.1 (1) F2.8					
EDR-92 POLE ID: 3462	232+60	225		(675) 3/0 ACSR (Pigeon) (225) 1/0 ACSR (Raven) (100) 2 AWG Triplex (Conch)	(1) 45-3	(1) CAL-1	(1) J2.1	(1) G1.5			(1) H1.1	(1) E1.1 (1) F2.8					
EDR-93 POLE ID: 20448	234+85	252		(756) 3/0 ACSR (Pigeon) (252) 1/0 ACSR (Raven)		(1) CAL-1 (1) A5.3NG (1) S1.1											
EDR-94 POLE ID: 20355	237+37	242	4° 57 ' 22" RT	(726) 3/0 ACSR (Pigeon) (242) 1/0 ACSR (Raven)		(1) CAL-6											

MASON COUNTY PUD 1										CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET													A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-95 POLE ID: 20447	239+79	301	8° 47 ' 38" RT	(903) 3/0 ACSR (Pigeon) (301) 1/0 ACSR (Raven)		(1) CAL-6	(1) J2.1					(3) E1.4					
EDR-96 POLE ID: 20441	242+80	217	4° 57 ' 0" RT	(652) 3/0 ACSR (Pigeon) (217) 1/0 ACSR (Raven)		(1) CAL-6						(2) E1.4					
EDR-97 POLE ID: 3519	244+97	306	11° 36 ' 18" RT	(918) 3/0 ACSR (Pigeon) (306) 1/0 ACSR (Raven)	(1) 40-3	(1) CAL-2						(3) E1.4					
EDR-98 POLE ID: 3521	248+03	207		(622) 3/0 ACSR (Pigeon) (207) 1/0 ACSR (Raven)	(1) 40-3	(1) C1.13L											
EDR-99 POLE ID: 20438	250+10	190		(571) 3/0 ACSR (Pigeon) (190) 1/0 ACSR (Raven)		(1) CAL-1											
EDR-100 POLE ID: 20442	252+01	203		(608) 3/0 ACSR (Pigeon) (203) 1/0 ACSR (Raven)		(1) CAL-1											
EDR-101 POLE ID: 20444	254+04	213	2° 10 ' 11" LT	(639) 3/0 ACSR (Pigeon) (213) 1/0 ACSR (Raven)		(1) CAL-6	(3) J2.1										
EDR-102 POLE ID: 20437	256+16	139		(416) 3/0 ACSR (Pigeon) (139) 1/0 ACSR (Raven)		(1) C6.21L											
EDR-103 POLE ID: 5802	257+55	139		(417) 3/0 ACSR (Pigeon) (139) 1/0 ACSR (Raven)		(1) CAL-1	(1) J2.1										
EDR-104 POLE ID: 24036	258+94	272		(817) 3/0 ACSR (Pigeon) (272) 1/0 ACSR (Raven)		(1) CAL-1	(2) J2.1										
EDR-105 POLE ID: 24035	261+67	264	2° 50 ' 54" RT	(791) 3/0 ACSR (Pigeon) (264) 1/0 ACSR (Raven)		(1) CAL-1											
EDR-106 POLE ID: 24034	264+30	341	4° 26 ' 18" RT	(1024) 3/0 ACSR (Pigeon) (341) 1/0 ACSR (Raven)		(1) CAL-1											

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET												A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES	
EDR-107 POLE ID: 20432	267+72	235		(705) 3/0 ACSR (Pigeon) (235) 1/0 ACSR (Raven)		(1) CAL-1										
EDR-108 POLE ID: 20430	270+07	362	2° 32 ' 31" LT	(1087) 3/0 ACSR (Pigeon) (362) 1/0 ACSR (Raven)		(1) CAL-1										
EDR-109 POLE ID: 20428	273+69	244	9° 12 ' 47" LT	(731) 3/0 ACSR (Pigeon) (244) 1/0 ACSR (Raven)		(1) CAL-2	(1) J2.1					(2) E1.1 (1) F2.8				
EDR-110 POLE ID: 20433	276+13	289		(866) 3/0 ACSR (Pigeon) (289) 1/0 ACSR (Raven)		(1) CAL-1	(1) J2.1									
EDR-111 POLE ID: 20431 POLE ID: 5394	279+02	229	9° 5 ' 19" RT	(688) 3/0 ACSR (Pigeon) (229) 1/0 ACSR (Raven)	(1) 30-4	(1) CAL-2	(2) J2.1					(1) E1.1 (1) E1.4 (1) F2.8				
EDR-112 POLE ID: 20426	281+31	289	11° 30 ' 57" RT	(868) 3/0 ACSR (Pigeon) (289) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-2						(3) E1.4				
EDR-113 POLE ID: 20425 POLE ID: 3458	284+20	232		(695) 3/0 ACSR (Pigeon) (232) 1/0 ACSR (Raven)	(1) 30-5	(1) CAL-6 (1) A5.3NG (1) S1.1	(2) J2.1					(1) E1.1 (1) E1.4 (1) F2.8				
EDR-114 POLE ID: 20424	286+52	228		(685) 3/0 ACSR (Pigeon) (228) 1/0 ACSR (Raven)		(1) CAL-6										
EDR-115 POLE ID: 20423	288+80	316	2° 31 ' 30" RT	(947) 3/0 ACSR (Pigeon) (316) 1/0 ACSR (Raven)		(1) CAL-6										
EDR-116 POLE ID: 20422	291+96	287	2° 6 ' 57" RT	(862) 3/0 ACSR (Pigeon) (287) 1/0 ACSR (Raven)		(1) CAL-6										
EDR-117 POLE ID: 20421 POLE ID: NEW STR	294+83	330	2° 29 ' 27" RT	(991) 3/0 ACSR (Pigeon) (330) 1/0 ACSR (Raven)		(1) CAL-6										
EDR-118 POLE ID: 20420	298+14	326		(977) 3/0 ACSR (Pigeon) (326) 1/0 ACSR (Raven)		(1) C6.21L										

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.				NO	REVISION		DATE	BY
													A	ISSUED FOR BID		9/4/26	BDR
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET																	
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES		
EDR-119 POLE ID: 20419	301+39	224	7° 7 ' 6" LT	(671) 3/0 ACSR (Pigeon) (224) 1/0 ACSR (Raven)		(1) C6.21L											
EDR-120 POLE ID: 20418	303+63	301	13° 44 ' 16" LT	(903) 3/0 ACSR (Pigeon) (301) 1/0 ACSR (Raven)		(1) CAL-2						(3) E1.1 (1) F2.8					
EDR-121 POLE ID: 20415	306+64	327	5° 31 ' 22" LT	(981) 3/0 ACSR (Pigeon) (327) 1/0 ACSR (Raven)		(1) CAL-2											
EDR-122 POLE ID: 20417	309+91	156		(469) 3/0 ACSR (Pigeon) (156) 1/0 ACSR (Raven)		(1) CAL-1 (1) A5.3NG (1) S1.1											
EDR-123 POLE ID: 5611	311+47	172		(515) 3/0 ACSR (Pigeon) (172) 1/0 ACSR (Raven)	(1) 45-4	(1) C6.21L (1) S2.32					(1) H1.1						
EDR-124 POLE ID: 20416	313+19	271		(814) 3/0 ACSR (Pigeon) (271) 1/0 ACSR (Raven)		(1) CAL-1											
EDR-125 POLE ID: 20414	315+90	317		(951) 3/0 ACSR (Pigeon) (317) 1/0 ACSR (Raven)		(1) CAL-6											
EDR-126 POLE ID: 20413	319+07	165		(496) 3/0 ACSR (Pigeon) (165) 1/0 ACSR (Raven)		(1) CAL-6											
EDR-127 POLE ID: NEW STR	320+73	139		(417) 3/0 ACSR (Pigeon) (139) 1/0 ACSR (Raven)													
EDR-128 POLE ID: 20412	322+12	316	9° 22 ' 45" LT	(948) 3/0 ACSR (Pigeon) (316) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-2						(2) E1.1 (1) F2.8					
EDR-129 POLE ID: 20411	325+28	280	6° 41 ' 49" LT	(841) 3/0 ACSR (Pigeon) (280) 1/0 ACSR (Raven)		(1) CAL-2						(2) E1.1 (1) F2.8					
EDR-130 POLE ID: 20410 POLE ID: 3565	328+08	238	8° 38 ' 23" RT	(714) 3/0 ACSR (Pigeon) (238) 1/0 ACSR (Raven)	(1) 45-2 (1) 35-4	(1) CAL-6						(1) E1.1 (3) E1.4 (1) F2.8					

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET												A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES	
EDR-131 POLE ID: 20409	330+46	302		(907) 3/0 ACSR (Pigeon) (302) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-6						(1) E1.1 (1) F2.8				
EDR-132 POLE ID: 20408 POLE ID: 3568	333+48	263	7° 1 ' 36" RT	(790) 3/0 ACSR (Pigeon) (263) 1/0 ACSR (Raven)	(1) 35-4	(1) CAL-2						(1) E1.1 (3) E1.4 (1) F2.8				
EDR-133 POLE ID: 5211 POLE ID: 3570	336+12	295	5° 16 ' 57" RT	(885) 3/0 ACSR (Pigeon) (295) 1/0 ACSR (Raven)	(1) 45-2 (1) 30-4	(1) CAL-2						(1) E1.1 (2) E1.4 (1) F2.8				
EDR-134 POLE ID: 5810	339+07	295		(884) 3/0 ACSR (Pigeon) (295) 1/0 ACSR (Raven)		(1) CAL-1										
EDR-135 POLE ID: 5992	342+01	306		(917) 3/0 ACSR (Pigeon) (306) 1/0 ACSR (Raven)	(1) 40-3	(1) C1.13L										
EDR-136 POLE ID: 20407	345+07	314		(941) 3/0 ACSR (Pigeon) (314) 1/0 ACSR (Raven)		(1) CAL-1										
EDR-137 POLE ID: 20406	348+21	327		(982) 3/0 ACSR (Pigeon) (327) 1/0 ACSR (Raven)		(1) CAL-1										
EDR-138 POLE ID: 20318	351+48	312		(936) 3/0 ACSR (Pigeon) (312) 1/0 ACSR (Raven)		(1) C1.13L										
EDR-139 POLE ID: 20405 POLE ID: NEW STR	354+60	282	2° 24 ' 44" RT	(845) 3/0 ACSR (Pigeon) (282) 1/0 ACSR (Raven)	(1) 50-2	(1) CAL-6						(1) E1.1 (1) F2.8		(1) M.FIBER	REMOVE EXISTING WOOD FIBER ALLEY ARM	
EDR-140 POLE ID: 20404	357+42	285		(856) 3/0 ACSR (Pigeon) (285) 1/0 ACSR (Raven)		(1) CAL-6						(1) E1.1		(1) M.FIBER	REMOVE EXISTING WOOD FIBER ALLEY ARM	
EDR-141 POLE ID: 20403	360+27	277		(830) 3/0 ACSR (Pigeon) (277) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-1										
EDR-142 POLE ID: 20402	363+04	337		(1010) 3/0 ACSR (Pigeon) (337) 1/0 ACSR (Raven)		(1) C6.21L (1) A5.3NG (1) S1.1						(1) E1.1 (1) F2.8				

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET												A	ISSUED FOR BID		9/4/26	BDR
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES	
EDR-143 POLE ID: 3583	366+40	281		(843) 3/0 ACSR (Pigeon) (281) 1/0 ACSR (Raven)	(1) 50-2	(1) C6.21L										
EDR-144 POLE ID: 20496	369+21	245	5° 28 ' 21" LT	(734) 3/0 ACSR (Pigeon) (245) 1/0 ACSR (Raven)		(1) CAL-2	(1) J2.1					(2) E1.1 (1) F2.8				
EDR-145 POLE ID: 20401	371+66	387	15° 21 ' 56" LT	(1161) 3/0 ACSR (Pigeon) (387) 1/0 ACSR (Raven)	(1) 50-2	(1) CAL-2						(2) E1.1 (1) F2.8				
EDR-146 POLE ID: 20497	375+53	341		(1024) 3/0 ACSR (Pigeon) (341) 1/0 ACSR (Raven)	(1) 50-3	(1) CAL-1										
EDR-147 POLE ID: NO#	378+95	330		(991) 3/0 ACSR (Pigeon) (330) 1/0 ACSR (Raven) (130) 2 AWG Triplex (Conch)	(1) 50-3	(1) CAL-1	(1) J2.1	(1) G1.5			(1) H1.1					
EDR-148 POLE ID: 20500	382+25	320		(959) 3/0 ACSR (Pigeon) (320) 1/0 ACSR (Raven)		(1) CAL-1										
EDR-149 POLE ID: 20397	385+45	357	15° 36 ' 3" RT	(1070) 3/0 ACSR (Pigeon) (357) 1/0 ACSR (Raven)	(1) 50-2	(1) CAL-2						(3) E1.1 (1) F2.8				
EDR-150 POLE ID: 20501	389+02	260	17° 10 ' 32" RT	(780) 3/0 ACSR (Pigeon) (260) 1/0 ACSR (Raven) (85) 4 AWG ACSR (Swanate)	(1) 50-2	(1) CAL-2 (1) A5.3NG (1) S1.1	(1) UK2.1	(1) G1.5			(1) H1.1	(3) E1.1 (1) F2.8				
EDR-151 POLE ID: 20499	391+62	292	2° 14 ' 43" RT	(875) 3/0 ACSR (Pigeon) (292) 1/0 ACSR (Raven)		(1) CAL-1 (1) A5.3NG (1) S1.1	(2) UK2.1									
EDR-152 POLE ID: 20354	394+53	348	33° 50 ' 35" LT	(1043) 3/0 ACSR (Pigeon) (348) 1/0 ACSR (Raven)		(1) CAL-2	(1) J2.1					(2) E1.1 (1) F2.8				
EDR-153 POLE ID: 20396	398+01	226	29° 28 ' 57" RT	(679) 3/0 ACSR (Pigeon) (226) 1/0 ACSR (Raven)	(1) 50-2	(1) CAL-2	(1) J2.1 (1) UK2.1	(1) G1.5			(1) H1.1	(2) E1.1 (1) F2.8				
EDR-154 POLE ID: 20400	400+28	292	5° 20 ' 36" LT	(875) 3/0 ACSR (Pigeon) (292) 1/0 ACSR (Raven)		(1) CAL-6						(2) E1.1 (1) F2.8				

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY									
												A	ISSUED FOR BID		9/4/26	BDR									
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET																									

STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES
EDR-155 POLE ID: 20502	403+19	254		(763) 3/0 ACSR (Pigeon) (254) 1/0 ACSR (Raven)		(1) CAL-6									
EDR-156 POLE ID: 20399 POLE ID: 3654	405+73	282	7° 18 ' 24" RT	(846) 3/0 ACSR (Pigeon) (282) 1/0 ACSR (Raven)	(1) 50-2 (1) 35-3	(1) CAL-6						(1) E1.1 (2) E1.4 (1) F2.8			
EDR-157 POLE ID: 20398 POLE ID: 3656	408+55	258	5° 22 ' 8" RT	(773) 3/0 ACSR (Pigeon) (258) 1/0 ACSR (Raven)	(1) 45-2 (1) 35-3	(1) CAL-6						(1) E1.1 (3) E1.4 (1) F2.8			
EDR-158 POLE ID: 20395	411+13	232	6° 43 ' 23" LT	(696) 3/0 ACSR (Pigeon) (232) 1/0 ACSR (Raven)		(1) CAL-1									
EDR-159 POLE ID: 20394	413+45	252		(757) 3/0 ACSR (Pigeon) (252) 1/0 ACSR (Raven)	(1) 45-3	(1) CAL-6									
EDR-160 POLE ID: 20504	415+97	289	5° 36 ' 18" RT	(867) 3/0 ACSR (Pigeon) (289) 1/0 ACSR (Raven)		(1) CAL-1						(3) E1.1 (1) F2.8			
EDR-161 POLE ID: 20505 POLE ID: 3661	418+86	299	8° 57 ' 23" RT	(898) 3/0 ACSR (Pigeon) (299) 1/0 ACSR (Raven)	(1) 45-2 (1) 30-4	(1) CAL-2						(1) E1.1 (2) E1.4 (1) F2.8			
EDR-162 POLE ID: NO#	421+86	207	24° 12 ' 1" LT	(620) 3/0 ACSR (Pigeon) (207) 1/0 ACSR (Raven)		(1) CAL-2						(3) E1.1 (1) F2.8			
EDR-163 POLE ID: 20507	423+93	252	8° 45 ' 18" RT	(757) 3/0 ACSR (Pigeon) (252) 1/0 ACSR (Raven)		(1) CAL-2	(1) J2.1					(2) E1.1 (1) F2.8			
EDR-164 POLE ID: 20392	426+45	220	2° 13 ' 16" RT	(659) 3/0 ACSR (Pigeon) (220) 1/0 ACSR (Raven)		(1) CAL-1									
EDR-165 POLE ID: NO#	428+65	279	19° 8 ' 26" LT	(838) 3/0 ACSR (Pigeon) (279) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-2						(2) E1.1 (1) F2.8			
EDR-166 POLE ID: 20508 POLE ID: NEW STR	431+44	265	18° 9 ' 7" RT	(795) 3/0 ACSR (Pigeon) (265) 1/0 ACSR (Raven)	(1) 45-2	(1) CAL-2						(2) E1.1 (1) F2.8			

MASON COUNTY PUD 1									CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.			NO	REVISION		DATE	BY
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET												A	ISSUED FOR BID		9/4/26	BDR

STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES
EDR-167 POLE ID: 20244	434+09	232	9° 29 ' 22" RT	(697) 3/0 ACSR (Pigeon) (232) 1/0 ACSR (Raven)		(1) CAL-2						(2) E1.1 (1) F2.8			
EDR-168 POLE ID: 20237	436+41	260	11° 40 ' 6" LT	(779) 3/0 ACSR (Pigeon) (260) 1/0 ACSR (Raven)		(1) CAL-1						(2) E1.1 (1) F2.8			
EDR-169 POLE ID: 20509 POLE ID: NEW STR	439+01	324	3° 54 ' 24" RT	(971) 3/0 ACSR (Pigeon) (324) 1/0 ACSR (Raven)		(1) CAL-2									
EDR-170 POLE ID: 20510	442+25	315		(946) 3/0 ACSR (Pigeon) (315) 1/0 ACSR (Raven)	(1) 45-3	(1) CAL-1									
EDR-171 POLE ID: 5798	445+40	304		(913) 3/0 ACSR (Pigeon) (304) 1/0 ACSR (Raven)	(1) 40-3	(1) C1.13L	(1) J2.1	(1) G1.5							
EDR-172 POLE ID: NO# POLE ID: 3694	448+44	321	3° 53 ' 25" RT	(963) 3/0 ACSR (Pigeon) (321) 1/0 ACSR (Raven)	(1) 45-3 (1) 35-4	(1) C6.21L (1) S2.32					(1) H1.1	(1) E1.1 (1) E1.4 (1) F2.8			
EDR-173 POLE ID: 20393 POLE ID: 3678	451+65	260	9° 6 ' 26" RT	(779) 3/0 ACSR (Pigeon) (260) 1/0 ACSR (Raven)	(1) 30-4	(1) CAL-2						(1) E1.1 (3) E1.4 (1) F2.8			
EDR-174 POLE ID: 20391 POLE ID: 3680	454+25	154	6° 49 ' 2" RT	(461) 3/0 ACSR (Pigeon) (154) 1/0 ACSR (Raven)	(1) 30-4	(1) CAL-2						(1) E1.1 (3) E1.4 (1) F2.8			
EDR-175 POLE ID: 20390	455+79	279	8° 27 ' 17" RT	(837) 3/0 ACSR (Pigeon) (279) 1/0 ACSR (Raven)		(1) CAL-2 (1) A5.3NG (1) S1.1	(3) J2.1								
EDR-176 POLE ID: 20524	458+58	321	8° 33 ' 51" RT	(963) 3/0 ACSR (Pigeon) (321) 1/0 ACSR (Raven)		(1) CAL-2 (1) A5.3NG (1) S1.1						(1) E1.1 (1) F2.8			
EDR-177 POLE ID: 20517	461+79	292		(877) 3/0 ACSR (Pigeon) (292) 1/0 ACSR (Raven)		(1) CAL-6	(2) J2.1								
EDR-178 POLE ID: 20523	464+71	250		(749) 3/0 ACSR (Pigeon) (250) 1/0 ACSR (Raven)		(1) CAL-1	(1) J2.1								

MASON COUNTY PUD 1												CONSTRUCTION NOTES: FIELD VERIFY ALL TRANSFER CONDUCTOR SIZES.				NO	REVISION		DATE	BY
																A	ISSUED FOR BID		9/4/26	BDR
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET																				
STRUCTURE NO.	STATION (FT)	AHEAD SPAN (FT)	PI / LINE ANGLE	CONDUCTOR & CONDUIT	POLE CLASS & LENGTH	PRIMARY DISTRIBUTION ASSEMBLIES	SECONDARY DISTRIBUTION ASSEMBLIES	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	UNDERGROUND DISTRIBUTION ASSEMBLIES	FOUNDATIONS & PADS	GROUNDING ASSEMBLIES	GUYING & ANCHOR ASSEMBLIES	CONDUCTOR ACCESSORIES	MISC. ASSEMBLIES	CONSTRUCTION NOTES					
EDR-179 POLE ID: 20516	467+21	358		(1073) 3/0 ACSR (Pigeon) (358) 1/0 ACSR (Raven) (70) 1/0 AWG Triplex (Netrina)	(1) 50-3	(1) CAL-1	(1) J2.1	(1) G1.5			(1) H1.1	(1) E1.1 (1) F2.8								
EDR-180 POLE ID: 20522 POLE ID: 3709	470+78	293		(880) 3/0 ACSR (Pigeon) (293) 1/0 ACSR (Raven) (50) 2 AWG Triplex (Conch)	(1) 50-3 (1) 30-7	(1) CAL-1	(2) J2.1	(1) G1.5			(1) H1.1	(1) E1.1 (1) F2.8								
EDR-181 POLE ID: 20515	473+72	310		(930) 3/0 ACSR (Pigeon) (310) 1/0 ACSR (Raven)		(1) CAL-6														
EDR-182 POLE ID: 20512	476+82	196	6° 29 ' 32" LT	(589) 3/0 ACSR (Pigeon) (196) 1/0 ACSR (Raven)		(1) CAL-2	(1) J2.1					(2) E1.1 (1) F2.8								
EDR-183 POLE ID: 3713	478+78	143	14° 27 ' 2" LT	(428) 3/0 ACSR (Pigeon) (143) 1/0 ACSR (Raven)	(1) 40-3	(1) CAL-2						(2) E1.1 (1) F2.8								
EDR-184 POLE ID: 3714	480+21		2° 29 ' 48" LT			(1) C6.21L														

MASON COUNTY PUD 1															NO.	REVISION					
ELDON-DUCKABUSH RECONDUCTOR DISTRIBUTION LINE REMOVAL STAKING SHEET SUMMARY															A	ISSUED FOR BID					
QTY	CONDUCTOR & CONDUIT	QTY	POLE CLASS & LENGTH	QTY	PRIMARY DISTRIBUTION ASSEMBLIES	QTY	SECONDARY DISTRIBUTION ASSEMBLIES	QTY	TRANSFORMERS, SWITCHGEARS, VAULTS, SECTORS	QTY	UNDERGROUND DISTRIBUTION ASSEMBLIES	QTY	FOUNDATION & PADS	QTY	GROUNDING ASSEMBLIES	QTY	GUYING & ANCHOR ASSEMBLIES	QTY	CONDUCTOR ACCESSORIES	QTY	MISCELLANEOUS ASSEMBLIES
75	4/0 AWG Triplex (Sweetbriar)	4	50-3	1	Y1.3	4	UK2.1	11	G1.5	1	UA1.2			13	H1.1	45	F2.8			2	M.FIBER
225	4 AWG ACSR (Swanate)	7	50-2	2	S2.32	37	J2.1			55	2AWG ALUMINUM URD CABLE					35	E1.4				
81051	3/0 ACSR (Pigeon)	1	45-4	1	S1.3											81	E1.1				
525	2 AWG Triplex (Conch)	7	45-3	12	S1.1																
70	1/0 AWG Triplex (Netrina)	11	45-2	22	CAL-6																
27018	1/0 ACSR (Raven)	1	40-4	31	CAL-2																
		7	40-3	34	CAL-1																
		1	35-5	9	C6.21L																
		3	35-4	4	C1.13L																
		2	35-3	12	A5.3NG																
		1	30-7																		
		1	30-5																		
		5	30-4																		